



kramer

VGAA-IN8-F64

8-Channel VGA with Analog Audio Input Card

| Kramer Core



VGAA-IN8-F64 is an eight-channel VGA with analog audio input card for the VS-6464 Series Modular Multi-Format Digital Matrix Switchers. The VGAA-IN8-F64 inputs eight VGA with analog audio signals into the chassis. Audio is accessed by connecting the supplied Kramer VGA with audio cables to each VGA port

FEATURES

- Max. Bandwidth - 450MHz
- HDTV Compatible
- Analog Audio Over Breakaway Connector



kramer

TECHNICAL SPECIFICATIONS

PORTS:	8 VGA on 15-pin HD connectors, 8 unbalanced analog audio on 3.5mm mini jack connectors (accessible via C GF/GMAF-30 cables)
BANDWIDTH:	450MHz
MAXIMUM RANGE:	10m (32ft)
POWER CONSUMPTION:	35W
OPERATING TEMPERATURE:	0° to +40°C (32° to 104°F)
STORAGE TEMPERATURE:	-40° to +70°C (-40° to 158°F)
HUMIDITY:	10% to 90%, RHL non-condensing
SAFETY REGULATORY COMPLIANCE:	CE
ENVIRONMENTAL REGULATORY COMPLIANCE:	Complies with appropriate requirements of RoHs and WEEE
INCLUDED ACCESSORIES:	8 C-GF/GMAF-30 cables
Product Dimensions	39.50cm x 18.00cm x 2.00cm (15.55" x 7.09" x 0.79") W, D, H
Product Weight	0.4kg (1.0lbs) approx
Shipping Dimensions	54.80cm x 27.50cm x 10.60cm (21.57" x 10.83" x 4.17") W, D, H
Shipping Weight	0.8kg (1.7lbs) approx